



Fujilamp_Projection Lamps

Detailed product specifications are available on: us.100y.com.tw

Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Focal distance (mm)	Avg life (H)	Color Temp (mm)	Fig. No.
BHB 120V 500W	BHB	120	250	65.8	50	3400	11

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	Filament Design	Ave. Life (hr)	ANSI
30662	BHB 120V250W	Fujilamp	Fujilamp_Projection Lamp	120V	250W	3400K	G7.9	50Hr	BHB



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
BLC 120V 30W	BLC	120	30	400	50	CC-2V	2

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	LumensLm	Filament Design	Ave. Life (hr)	ANSI
30967	BLC 120V30W	Fujilamp	Fujilamp_Projection Lamp	120V	30W	2775K	400Lm	BA15d	50Hr	BLC



Lamp Type	ANSI	Rated voltages (V)	Amp.	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
BRK 4V 0.75A	BRK	4	0.75	30	50	C-8	5

Part No.	Product No.	Manufacturer	Description	Voltage (V)	LumensLm	Filament Design	Ave. Life (hr)	ANSI
31036	BRK-4V0.75A	Fujilamp	Fujilamp_Projection Lamp	4V	30Lm	P30s	50Hr	BRK



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
BRP 100V 750W	BRP	100	750	—	50	*C-13D	2
BRP 120V 750W	BRP	120	750	—	50	*C-13D	2
BRR 120V 1000W	BRR	120	1000	—	50	*C-13D	2
BRN 120V 1200W	BRN	120	1200	—	20	*C-13D	2

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	Filament Design	Ave. Life (hr)	ANSI
30825	BRN 120V1200W	Fujilamp	Fujilamp_Projection Lamp	120V	1200W	3350K	G17t-7	20Hr	BRN
30821	BRP 100V750W	Fujilamp	Fujilamp_Projection Lamp	100V	750W	3300K	G17t-7	50Hr	BRP
30822	BRP 120V750W	Fujilamp	Fujilamp_Projection Lamp	120V	750W	3300K	G17t-7	50Hr	BRP
30824	BRR 120V1000W	Fujilamp	Fujilamp_Projection Lamp	120V	1000W	3250K	G17t-7	50Hr	BRR



Lamp Type	ANSI	Rated voltages (V)	Amp.	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
BRS 4V 0.75A	BRS	4	0.75	30	50	C-6	2
BSK 6V 1A	BSK	6	1	70	100	C-6	2
BSS/BSB 6V 1A	BSS/BSB	6	1	70	100	C-8	5
BSW 7V 0.2A	BSW	7	0.2	13	50	C-8	5

Part No.	Product No.	Manufacturer	Description	Voltage (V)	LumensLm	Filament Design	Ave. Life (hr)	ANSI
31032	BRS-4V0.75A	Fujilamp	Fujilamp_Projection Lamp	4V	30Lm	P30s	50Hr	BRS
31037	BSK-6V1A	Fujilamp	Fujilamp_Projection Lamp	6V	70Lm	P30s	100Hr	BSK
31038	BSS/BSB-6V1A	Fujilamp	Fujilamp_Projection Lamp	6V	70Lm	P30s	100Hr	BSS/BSB
31039	BSW-7V0.2A	Fujilamp	Fujilamp_Projection Lamp	7V	13Lm	P30s	50Hr	BSW



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
BTG 120V 1200W	BTG	120	1200	38200	20	C-13D	1
BTG 120V 1200WF	BTG	120	1200	38000	20	C-13D	1

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	LumensLm	Filament Design	Ave. Life (hr)	ANSI
30827	BTG 120V1200W	Fujilamp	Fujilamp_Projection Lamp	120V	1200W	3350K	38200Lm	G17t-7	20Hr	BTG
30829	BTG 120V1200WF	Fujilamp	Fujilamp_Projection Lamp	120V	1200W	3350K	38000Lm	G17t-7	20Hr	BTG



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
BTL 120V 500W	BTL	120	500	13000	300	CC-8	19
BTM 120V 500W	BTM	120	500	13000	100	C-13D	20
BTN 120V 750W	BTN	120	750	17000	500	C-13D	20
BTP 120V 750W	BTP	120	750	20000	200	C-13D	20
BTP 120V 1000W	BTP	120	1000	27500	200	C-13D	20

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	LumensLm	Filament Design	Ave. Life (hr)	ANSI
30776	BTL 120V500W	Fujilamp	Fujilamp_Projection Lamp	120V	500W	3050K	11000Lm	P28s	500Hr	BTL
30780	BTM 120V500W	Fujilamp	Fujilamp_Projection Lamp	120V	500W	3200K	13000Lm	P28s	100Hr	BTM
30784	BTN 120V750W	Fujilamp	Fujilamp_Projection Lamp	120V	750W	3050K	17000Lm	P28s	500Hr	BTN
30790	BTP 120V1000W	Fujilamp	Fujilamp_Projection Lamp	120V	1000W	3200K	27500Lm	P28s	200Hr	BTP
30788	BTP 120V750W	Fujilamp	Fujilamp_Projection Lamp	120V	750W	3200K	20000Lm	P28s	200Hr	BTP

