



Fujilamp_Projection Lamps

Detailed product specifications are available on: us.100y.com.tw

Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Focal distance (mm)	Color temp (K)	Avg life (H)	Fig. No.
DDK 19V 80W	DDK	19	80	152.4	40	CC-6	7
DDL 20V 150W	DDL	20	150	194.5	500	CC-6	7
DDM 19V 80W	DDM	19	80	152.4	50	CC-6	7

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	Filament Design	Ave. Life (hr)	ANSI
30583	DDK 19V 80W	Fujilamp	Fujilamp_Projection Lamp	19V	80W	3300K	GX5.3	40Hr	DDK
30599	DDL 20V 150W	Fujilamp	Fujilamp_Projection Lamp	20V	150W	3150K	GX5.3	500Hr	DDL
30584	DDM 19V 80W	Fujilamp	Fujilamp_Projection Lamp	19V	80W	3350K	GX5.3	50Hr	DDM



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
DDN 20V 170W	FCK	20	170	4250	100	CC-8	1

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	LumensLm	Filament Design	Ave. Life (hr)	ANSI
30868	DDN 20V200W	Fujilamp	Fujilamp_Projection Lamp	20V	200W	3150K	5000Lm	R7s	100Hr	DDN



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
DDP 22V 132W	DDP	22	132	3900	125	CF-6	10

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	LumensLm	Filament Design	Ave. Life (hr)	ANSI
30711	DDP 22V132W	Fujilamp	Fujilamp_Projection Lamp	22V	132W	3250K	3900Lm	GY9.5	125Hr	DDP



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Focal distance (mm)	Avg life (H)	Filament	Fig. No.
DDS 21V 80W	DDS	21	80	165	500	CC-6	7
DED 13.8V 85W	DED	13.8	85	165.0	1000	CC-6	7
DJT 13.8V 50W	DJT	13.8	50	152	1000	CC-6	7
DNE 12V 150W	DNE	120	150	69.1	12	—	11
DNF 21V 150W	DNF	21	150	69.1	25	—	10

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	Filament Design	Ave. Life (hr)	ANSI
30588	DDS 21V 80W	Fujilamp	Fujilamp_Projection Lamp	21V	80W	3125K	GX5.3	500Hr	DDS
30592	DED13.8V 85W	Fujilamp	Fujilamp_Projection Lamp	13.8V	85W	3150K	GX5.3	1000Hr	DED
30580	DJT 13.8V 50W	Fujilamp	Fujilamp_Projection Lamp	13.8V	50W	3150K	GX5.3	1000Hr	DJT
30661	DNE 24V250W	Fujilamp	Fujilamp_Projection Lamp	24V	250W	3350K	G7.9	12Hr	DNE
30654	DNF 21V150W	Fujilamp	Fujilamp_Projection Lamp	21V	150W	3400K	GX7.9	25Hr	DNF



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
DNS/FMC 120VW 500W	DNS/FMC	120	500	11000	500	C-13D	20
DNT/FMD 120V 750W	DNT/FMD	120	750	17000	500	C-13D	20
DNV/FME 120V 1000W	DNV/FME	120	1000	27500	200	C-13D	20
DPY 120W 5000W	DPY	120	5000	140000	500	C-13	13

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	LumensLm	Filament Design	Ave. Life (hr)	ANSI
30777	DNS/FMC 120V 500W	Fujilamp	Fujilamp_Projection Lamp	120V	500W	3050K	11000Lm	P28s	500Hr	P28s
30786	DNT/FMD 120V750W	Fujilamp	Fujilamp_Projection Lamp	120V	750W	3050K	17000Lm	P28s	500Hr	DNT/FMD
30792	DNV/FME 20V1000W	Fujilamp	Fujilamp_Projection Lamp	20V	1000W	3200K	27500Lm	P28s	200Hr	DNV/FME
30770	DPY 120V5000W	Fujilamp	Fujilamp_Projection Lamp	120V	5000W	3200K	140000Lm	G38	500Hr	DPY



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
DRA 120V 300W	DRA	120	300	6900	300	CC-6	3

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	LumensLm	Filament Design	Ave. Life (hr)	ANSI
30733	DRA 120V300W	Fujilamp	Fujilamp_Projection Lamp	120V	300W	3100K	6900Lm	G6.35	300Hr	DRA



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
DTY 120V 10000W	DTY	120	10000	285000	300	C-13	14

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	LumensLm	Filament Design	Ave. Life (hr)	ANSI
30772	DTY 120V10000W	Fujilamp	Fujilamp_Projection Lamp	120V	10000W	3200K	285000Lm	G38	300Hr	DTY

