



Fujilamp_Projection Lamps

Detailed product specifications are available on: us.100y.com.tw

Lamp Type	ANSI	Rated voltages (V)	Power Consumption(W)	Focal distande (mm)	Avg life (H)	Filament	Fig. No.
EMM 24V 250W	EMM	24	250	65.8	25	—	10
ENG 120V 300W	ENG	120	300	152.4	15	CC-8	8
ENH 120V 250W	ENH	120	250	152.4	175	CC-8	8
ENW 19V 80W	ENW	19	80	44.5	200	C-8	7
ENX 82V 360W	ENX	82	360	298.5	75	CC-8	8
ENX-5 86V 360W	ENX-5	86	360	298.5	75	CC-8	8
ENZ 30V 50W	ENZ	30	50	29	25	CC-6	7
EPF 30V 80W	EPF	30	80	78.4	100	—	10
EPG 21V 80W	EPG	21	80	78.4	100	—	10
EPN 12V 35W	EPN	12	35	29	50	C-6	7

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	Filament Design	Ave. Life (hr)	ANSI
3 0660	EMM 24V250W	Fujilamp	Fujilamp_Projection Lamp	24V	250W	3400K	GX7.9	25Hr	EMM
30635	ENG120V300W	Fujilamp	Fujilamp_Projection Lamp	120V	300W	3450K	GY5.3	15Hr	ENG
30630	ENH120V250W	Fujilamp	Fujilamp_Projection Lamp	120W	250W	3250K	GY5.3	175Hr	ENH
30587	ENW 19V 80W	Fujilamp	Fujilamp_Projection Lamp	19V	80W	3200K	GX5.3	200Hr	ENW
30639	ENX-5 86V360W	Fujilamp	Fujilamp_Projection Lamp	86V	360W	3300K	GY5.3	75Hr	ENX-5
30638	ENX82V360W	Fujilamp	Fujilamp_Projection Lamp	82V	360W	3300K	GY5.3	75Hr	ENX
30582	ENZ 30V 50W	Fujilamp	Fujilamp_Projection Lamp	30V	50W	3400K	GX5.3	25Hr	ENZ
30649	EPF 30V80W	Fujilamp	Fujilamp_Projection Lamp	30V	80W	3200K	GX7.9	100Hr	EPF
30648	EPG 21V80W	Fujilamp	Fujilamp_Projection Lamp	21V	80W	3300K	GX7.9	100Hr	EPG
30578	EPN 12V 35W	Fujilamp	Fujilamp_Projection Lamp	12V	35W	3300K	GX5.3	50Hr	EPN



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Total lumen (lm)	Avg life (H)	Filament	Fig. No.
EPR 120V 500W	EPR	120	500	—	50	*C-13D	4
EPS 220V 500W	EPS	220	500	—	50	*C-13D	4
EPS 240V 500W	EPS	240	500	—	50	*C-13D	4

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	Filament Design	Ave. Life (hr)	ANSI
30814	EPR 120V500W	Fujilamp	Fujilamp_Projection Lamp	120V	500W	3250K	G17t-7	50Hr	EPR
30815	EPS 220V500W	Fujilamp	Fujilamp_Projection Lamp	220V	500W	3200K	G17t-7	50Hr	EPS
30816	EPS 240V500W	Fujilamp	Fujilamp_Projection Lamp	240V	500W	3200K	G17t-7	50Hr	EPS



Lamp Type	ANSI	Rated voltages (V)	Power Consumption (W)	Focal distande (mm)	Avg life (H)	Filament	Fig. No.
EPT 10.8V 42W	EPT	10.8	42	38.1	8000	CC-6	7
EPV 14.5V 90W	EPV	14.5	90	155.2	500	CC-6	7
EPW 100V 360W	EPW	100	360	298.5	75	CC-8	8
EPX 14.5V 90W	EPX	14.5	90	165.1	500	CC-6	7
EPZ 13.8V 50W	EPZ	13.8	50	108	1000	CC-6	7
ERV 36V 340W	ERV	36	340	298.5	75	CC-8	7
ESD 12V 150W	ESD	120	150	44.5	12	CC-8	8
ESH 82V 85W	ESH	82	85	152.0	250	CC-8	8
ETJ 120V 250W	ETJ	120	250	36.5	175	CC-8	8
EVW 82V 250W	EVW	82	250	298.5	50	CC-8	8
EFW 24V 200W	EFW	24	200	298.5	50	CC-6	7
EWG 120V 300W	EWK	120	300	31.7	35	CC-8	8
EXX 120V 250W	EXX	120	250	—	25	CC-8	8
EYA 82V 200W	EYA	82	200	38.1	50	CC-8	8

Part No.	Product No.	Manufacturer	Description	Voltage (V)	Watts (W)	Color(K)	Filament Design	Ave. Life (hr)	ANSI
30579	EPT 10.8V 42W	Fujilamp	Fujilamp_Projection Lamp	10.8V	42W	2900K	GX5.3	8000Hr	EPT
30595	EPV 14.5V 90W	Fujilamp	Fujilamp_Projection Lamp	14.5V	90W	3150K	GX5.3	500Hr	EPV
30640	EPW100V360W	Fujilamp	Fujilamp_Projection Lamp	100V	360W	3300K	GY5.3	75Hr	EPW
30593	EPX 14.5V 90W	Fujilamp	Fujilamp_Projection Lamp	14.5V	90W	3150K	GX5.3	500Hr	EPX
30581	EPZ 13.8V 50W	Fujilamp	Fujilamp_Projection Lamp	13.8V	50W	3150K	GX5.3	1000Hr	EPZ
30610	ERV36V340W	Fujilamp	Fujilamp_Projection Lamp	36V	340W	3300K	GX5.3	75Hr	ERV
30627	ESD12V150W	Fujilamp	Fujilamp_Projection Lamp	12V	150W		GY5.3	12Hr	ESD
30625	ESH82V85W	Fujilamp	Fujilamp_Projection Lamp	82V	85W		GY5.3	250Hr	ESH

