

Multimeters & Panel Meters

APPA_Series Digit Multimeters

Detailed product specifications are available on: us.100y.com.tw



Part No.	Product No.	Manufacturer	Description	Range Manual/Auto	Buzzer Yes/No	Auto power Y/N	Batt.Test Y/N	Diode Y/N
7483	APPA-97	APPA	Digital Multimeter	Auto	Yes	Yes	No	Yes



Replacement test lead for APPA 30/60/90/100/200 series, Hard tips Comfort-grip, safety-shrouded, right-angle plug, 48" (1.2m), 1000V, 10A, CAT III.

Part No.	Product No.	Manufacturer	Description
26498	ATL-3	APPA	APPA-101

CHY_Multimeters and Accessories

CHY_Multimeter Series

Detailed product specifications are available on: us.100y.com.tw



Part No.	Product No.	Manufacturer	Description	Manual/Auto
20518	CHY-14	Chy	3 1/2 Digital Multimeter	Auto-Range



- LCD display 3 1/2 digits
- Easy to check components with a baseboard and alligator clips
- Ranges: 200 & 2000 pF / 20 y 200 nF / 2, 20, 200 & 2000 μF (9 scales)
- Test voltage: 3,2 V max.
- Basic accuracy: ±(0,5% + 1 digito)
- Low battery indicator
- Over range indicator
- Residual capacity adjust
- Fuse protected
- Alligator clips
- Power source: 1 battery 9V 6F22 type
- CE
- Dimensions: 151 x 70 x 38 mm

Part No.	Product No.	Manufacturer	Description	Manual/Auto	Capacitance	Auto power off
11118	CHY-15	Chy	3-1/2 Digital Capacitance Meter	Manual	0.1pf-20mf	NO



- Capacitance: 0-2000p/20n/200n/2u/20uF±2%
- Frequency: 1Hz~15MHz±0.1%
- DCV: 0~200m/2/20/200/600V±0.5%
- ACV: 0~200m/2/20/200/600V±1.5%
- DCA: 0-2m/20m/200mA/10A±2%
- ACA: 0-2m/20m/200mA/10A±2.5%
- Ω: 0-200/2K/20K/200K/2000K/20M±1%

Part No.	Product No.	Manufacturer	Description	Manual/Auto	Capacitance
20519	CHY-17	Chy	3 1/2 Digital Multimeter	Auto	2000pF 20nF 200Nf 2F 20F



- DCV: 0-320m/3.2/32/320/600V±1.2%
- ACV: 0-320m/3.2/32/320/600V±2%
- DCA: 0-32u/3.2m/32m/320m±2%/10A±3%
- ACA: 0-320u/3.2m/32m/320m±2.5%/10A±3%
- Ω: 0-310/3.1K/31K/310K/3.1M/31M±1.5%
- SIZE: 151 (H) x70 (W) x38 (D) mm

Part No.	Product No.	Manufacturer	Description	Manual/Auto
20520	CHY-19	Chy	3200 Auto-Range Digital Multimeter	Auto



- Voltage: DC400m/4/40/400/1000V AC 400m/4/40/400/750V DC±(0.5%+1dgt) AC±(1%+4dgt)
- Current: 4m/400m/10A DC±(1%+1dgt) AC±(1.5%+4dgt)
- Capacitance: 400/4K/40K/400K/4000K/40M±/4000MΩ±(0.8%+2dgt)
- Capacitance: 4n/40n/400n/4u/400uF
- Inductance: 4m/40m/400m/4/40H±(5%+10dgt)
- Frequency: 1Hz~4MHz±(0.1%+1dgt)
- SIZE: 200Hx900Wx40D/mm

Part No.	Product No.	Manufacturer	Description	Manual/Auto	Capacitance
20658	CHY-21	Chy	LCR Logic Digital Multimeter	Auto	4nF, 40nF, 400nF, 4uF, 400uF



T E L : Taiwan: 886-3-5753170
F A X : Taiwan: 886-3-5753172
E-mail: Taiwan: us_sale@100y.com.tw

Shenzhen: 86-755-83298787
Shenzhen: 86-755-83640655
Shenzhen: 100y@163.com

Shanghai: 86-21-54151736
Shanghai: 86-21-64605107
Shanghai: 100y-1@163.com