

Multimeters & Panel Meters

CHY_Multimeter Series

Detailed product specifications are available on: us.100y.com.tw



- DC Voltage: 0V~1000V $\pm(0.05\% \text{ rdg} + 4\text{digit})$
- AC Voltage: 20mV~750V $\pm(1.5\% \text{ rdg} + 10\text{digit})$
- AC Current: 0A~10A $\pm(2.5\% \text{ rdg} + 10\text{digit})$
- DC Current: 0A~10A $\pm(2\% \text{ rdg} + 10\text{digit})$
- Resistance: 0 Ω ~20M Ω $\pm(2\% \text{ rdg} + 3\text{digit})$

Part No.	Product No.	Manufacturer	Description
20521	CHY-23	Chy	Digital Multimeter



- DC Voltage: 200m/2/20/200/1000V $\pm(0.05\%+4\text{dgt})$
- Input resistance: 10M Ω
- AC Voltage: 200m/2/20V
- Current: 200u/2m/20m/200m/10A DC $\pm(0.5\%+10\text{d})$ AC $\pm(0.75\%+10\text{d})$
- Resistance: 20/200/2K/20K/200K/2M Ω $\pm(0.2\%+2\text{dgt})/20\text{M}\Omega\pm(2\%+3\text{dgt})$
- SIZE: 200H x 90W x 40D/mm

Part No.	Product No.	Manufacturer	Description
35297	CHY-23T	Chy	Digital Multimeter



Part No.	Product No.	Manufacturer	Description	Manual/Auto	Capacitance
20522	CHY-26	Chy	3 1/2 Digital Multimeter	Auto	200pF 2Nf 20nF 200nF 2F 200F



- Voltage: DC430m/4.3/43/430/1000V AC430m/4.3/43/430/750V DC $\pm(0.25\%+1\text{dgt})$ AC $\pm(0.75\%+2\text{dgt})$
- Current: 430u/43m/430m/10A DC $\pm(0.5\%+1\text{dgt})$ AC $\pm(1\%+2\text{dgt})$
- Resistance: 430/4.3K/43K/430K/4300K/43M $\Omega\pm(0.3\%+3\text{dgt})$
- Capacitance: 4.3n/43n/430n/4.3u/430uF
- Inductance: 4.3m/43m/430m/4.3/43H $\pm(5\%+10\text{dgt})$
- Frequency: 0.1Hz~430KHz $\pm(1\%+3\text{dgt})$
- Temperature: -20~1370 $^{\circ}\text{C}\pm(2\%+3\text{dgt})$

Part No.	Product No.	Manufacturer	Description	Manual/Auto	Capacitance	Auto power off
39369	CHY-29	Chy	Multimeter	Auto-Range	4.3n/43n/430n/4.3u/430uF	Yes



CHY-36A
CHY-36B



CHY-36C



CHY-38

Part No.	Product No.	Manufacturer	Description	Capacitance	Auto power off
20523	CHY-36A	Chy	CHY-Multimeter Series		
20524	CHY-36B	Chy	CHY-Multimeter Series		
20525	CHY-36C	Chy	Digital Multimeter		No
20526	CHY-38	Chy	Digital Multimeter	2nF, 20nF, 200nF, 2uF, 20uF	No



- Resistance: 20/200/2K/20K/200K/2M/20M Ω $\pm(0.5\%+3\text{dgt})$
- Capacitance: 2000p/20n/200n/2000nF/20u/200u/2000u/20mF
- Inductance: 2000u/20m/200m/2000mH/20H/200H/2000H/20000H
- Test frequency: 120Hz/1KHz choice
- SIZE: 192H*91W*53D/mm

Part No.	Product No.	Manufacturer	Description
29252	CHY-41R	Chy	LCR Logic Digital Multimeter

- We provide a wide range of products to development and maintenance engineers in all type of business
- If you cannot find the components you want on the catalogue, please call us.



Taiwan: 886-3-5753170

Shanghai: 021-54151736 Shenzhen: 0755-83298787

Centenary Materials

Waiting for your phone call



T E L : Taiwan: 886-3-5753170
F A X : Taiwan: 886-3-5753172
E-mail: Taiwan: us_sale@100y.com.tw

Shenzhen: 86-755-83298787
Shenzhen: 86-755-83640655
Shenzhen: 100y@163.com

Shanghai: 86-21-54151736
Shanghai: 86-21-64605107
Shanghai: 100y-1@163.com