

Multimeters & Panel Meters

CHY_Multimeter Series

Detailed product specifications are available on: us.100y.com.tw



- DCV: 0~400mV/4/40/400/600V±0.25%
- ACV: 0~400mV/4/40/400/600V±0.75%
- DCA: 0~4m/40m/400mA/10A±0.5%
- ACA: 0~4m/40m/400mA/10A±1%
- Ω: 0~400/4K/40K/400K/4M/40M±0.3%
- Frequency: 100HZ/1K/10K/100K/700KHZ±0.05%
- Capacitance: 0~40nf/40nf~20uf±2%/200uf±5%

Part No.	Product No.	Manufacturer	Description	Manual/Auto	Capacitance	Auto power off
20532	CHY-42	Chy	Auto-Range Multimeter	Auto	4nF, 40nF, 400nF, 4uF, 40uF	Yes



- DCV: 0~320mV/3.2/32/320/600V±0.3%
- ACV: 0~320mV/3.2/32/320/600V±1%
- DCA: 0~320u/3.2m/32m/320m/±0.5%/10A
- ACA: 0~320uA/32mA±1.5%/10A±2%
- Ω: 0~310/3.1K/31K/310K/3.1M/31M±0.4%
- Capacitance: 0~3.2/32/320nF±2%
- Size: 151 (H) x70 (W) x38 (D) mm

Part No.	Product No.	Manufacturer	Description	Capacitance
20533	CHY-47	Chy	Auto-Range Multimeter	3.2nF, 32nF, 320nF, 3.2F, 32F



- DCV: 0~200mV/2/20/200/600V±0.35%
- ACV: 0~200mV/600V±1%
- DCA: 0~200u/20m/200m/10A±0.5%
- Ω: 0~200/2K/20K/200K/2M/20M±0.4%
- Temperature: -20°C~750°C±2~3% (Include temperature rate)
- Frequency: 0~15MHZ±0.1%
- Capacitance: 0~2n/200nF/20uF±2%

Part No.	Product No.	Manufacturer	Description	Capacitance
20534	CHY-48C	Chy	Multimeter	2nF, 200nF, 20uF



- Operating environment: temp: 0~40°C, related humidity: <70%
- Storage environment: temp: -20°C ~ 60°C, related humidity <80%
- Power: 9V*1 (NEDA 1604, JIS 006P, IEC 6F22)
- Size: 19.2cm*9.1cm*5.25cm
- Weight: about 335g (include battery)

Part No.	Product No.	Manufacturer	Description
38648	CHY-48R	Chy	CHY-48R Multilogger

Multimeter Series Other Type Multimeters

Detailed product specifications are available on: us.100y.com.tw



320 Series	Range	61-320	61-322	61-324
		Based on accuracy		
AC Voltage	400.0m/4.000/40.00/400.0/750V	0.9%	1.2%	1.2%
DC Voltage	400.0m/4.000/40.00/400.0/1000V	0.5%	0.5%	0.5%
AC Current	400.0u/4000u/40.00m/400mA	--	1.5%	1.5%
DC Current	400.0u/4000u/40.00m/400mA	1.0% *	1.0%	1.0%
Resistance	400.0/4.000k/40.00k/400.0k/4.000M/40.00MΩ	0.7%	0.7%	0.7%
Capacitance	4.000n/40.00n/400.0n/4.000u/40.00u/400.0u/4.000m/40.00mF	2.0%	2.0%	2.0%
Frequency	4.000k/40.00k/400.0k/4.000M/40.00MHZ	0.01%	0.01%	0.01%

Part No.	Product No.	Manufacturer	Description
48430	61-320	IDEAL	IDEAL_Digital Multimeters
48432	61-322	IDEAL	IDEAL_True RMS Digital Multimeters
48433	61-324	IDEAL	IDEAL_True RMS Digital Multimeters

- We provide a wide range of products to development and maintenance engineers in all type of business
- If you cannot find the components you want on the catalogue, please call us.



Taiwan: 886-3-5753170
Shanghai: 021-54151736 Shenzhen: 0755-83298787

Centenary Materials
Waiting for your phone call



T E L : Taiwan: 886-3-5753170
F A X : Taiwan: 886-3-5753172
E-mail: Taiwan: us_sale@100y.com.tw

Shenzhen: 86-755-83298787
Shenzhen: 86-755-83640655
Shenzhen: 100y@163.com

Shanghai: 86-21-54151736
Shanghai: 86-21-64605107
Shanghai: 100y-1@163.com