

# Multimeters & Panel Meters

## Other Type Multimeters

Detailed product specifications are available on: [us.100y.com.tw](http://us.100y.com.tw)



- Voltage: DCV:200mV/2000mV/20V/200V/1000V ACV:200V/750V
- Current: DCA:200μA/2000μA/20mA/200mA/10A
- Resistance: Ohms:200/2000/20K/200K/2000KΩ

Part No.	Product No.	Description
14837	MT-903B	Digital Multimeter



Part No.	Product No.	Manufacturer	Description
41299	PC20	SANWA	Sanwa_Digital Multimeter
41303	PC500	SANWA	SANWA_multimeter
41308	PC5000	SANWA	SANWA_TRUE RMS Digital Multimeter
41305	PC510	SANWA	SANWA_Digital Multimeter

## BRYMEN Multimeters and Accessories BRYMEN\_BM850 5-4/5d Professional Multimeter Series

Detailed product specifications are available on: [us.100y.com.tw](http://us.100y.com.tw)



Part No.	Product No.	Manufacturer	Description	Manual/Auto	Capacitance	Auto power off
15713	BM-857	BRYMEN	BRYMEN_Digital Multimeter	AUTO	10pF to 9999F	YES
15712	BM-859CF	BRYMEN	BRYMEN_Digital Multimeter	AUTO	10pF to 9999F	YES



Part No.	Product No.	Manufacturer	Description
16789	BR-859X	BRYMEN	"BRYMEN" For BM850 Series Cable

## BRYMEN\_BM510 3-4/5d Mobil-Logger Professional Multimeter Series

Detailed product specifications are available on: [us.100y.com.tw](http://us.100y.com.tw)



- Temperature measurement: -50°C to 1000°C 0.3%+3d
- Capacitance: 10pF to 9999μF 0.8% +3d
- Frequency: 5Hz to 125KHz 0.01%+2d
- Resistance: 0.01Ω to 50MΩ 0.1%+2d
- DC Voltage: 0.01mV to 1000V 0.06%+2d True RMS
- AC Voltage: 0.01mV to 1000V 0.5%+3d
- DC Current: 0.1μA to 10A 0.2%+4d
- AC Current: 0.1μA to 10A 0.6%+3d True RMS

Part No.	Product No.	Manufacturer	Description	Manual/Auto	Capacitance	Auto power off
15686	BM-515	BRYMEN	BRYMEN_Digital Multimeter/Datalogger 3/4/5	Auto	10pF TO 9999F	YES

## BRYMEN\_BM810 3-4/5d Professional Multimeter Series

Detailed product specifications are available on: [us.100y.com.tw](http://us.100y.com.tw)



BM-812



BM-815

- Temperature measurement: -50°C to 1000°C 0.3%+3d
- Capacitance: 10pF to 9999μF 0.8% +3d
- Frequency: 5Hz to 125KHz 0.01%+2d
- Resistance: 0.01Ω to 50MΩ 0.1%+2d
- DC Voltage: 0.01mV to 1000V 0.06%+2d
- AC Voltage: 0.01mV to 1000V True RMS 0.5%+3d (BM-811, BM-815: AVE)
- DC Current: 0.1μA to 10A 0.2%+4d
- AC Current: 0.1μA to 10A True RMS 0.6%+3d (BM-811, BM-815: AVE)



BM-817

Part No.	Product No.	Manufacturer	Description	Manual/Auto	Capacitance	Auto power off
15711	BM-812	BRYMEN	BRYMEN_3/4/5 5000 Count Digital Multimeter	Auto	10pF to 9999F	Yes
23791	BM-815	BRYMEN	BRYMEN_3-4/5D Professional Multimeter + RS232PC Interface	Auto	10pF to 9999F	Yes
15200	BM-817	BRYMEN	BRYMEN_Digital 3-4/5d Professional Multimeter	Auto	10pF to 9999F	Yes

